

Control Characters

Char	Oct	Dec	Hex	Control-Key	Control Action
NUL	0	0	0	^@	Null character
SOH	1	1	1	^A	Start of heading, = console interrupt
STX	2	2	2	^B	Start of text, maintenance mode on HP console
ETX	3	3	3	^C	End of text
EOT	4	4	4	^D	End of transmission, not the same as ETB
ENQ	5	5	5	^E	Enquiry, goes with ACK; old HP flow control
ACK	6	6	6	^F	Acknowledge, clears ENQ logon hand
BEL	7	7	7	^G	Bell, rings the bell...
BS	10	8	8	^H	Backspace, works on HP terminals/computers
HT	11	9	9	^I	Horizontal tab, move to next tab stop
LF	12	10	a	^J	Line Feed
VT	13	11	b	^K	Vertical tab
FF	14	12	c	^L	Form Feed, page eject
CR	15	13	d	^M	Carriage Return
SO	16	14	e	^N	Shift Out, alternate character set
SI	17	15	f	^O	Shift In, resume defaultn character set
DLE	20	16	10	^P	Data link escape
DC1	21	17	11	^Q	XON, with XOFF to pause listings; ":okay to send".
DC2	22	18	12	^R	Device control 2, block-mode flow control
DC3	23	19	13	^S	XOFF, with XON is TERM=18 flow control
DC4	24	20	14	^T	Device control 4
NAK	25	21	15	^U	Negative acknowledge
SYN	26	22	16	^V	Synchronous idle
ETB	27	23	17	^W	End transmission block, not the same as EOT
CAN	30	24	17	^X	Cancel line, MPE echoes !!!
EM	31	25	19	^Y	End of medium, Control-Y interrupt
SUB	32	26	1a	^Z	Substitute
ESC	33	27	1b	^[Escape, next character is not echoed
FS	34	28	1c	^\ ^_	File separator
GS	35	29	1d	^] ^_	Group separator
RS	36	30	1e	^^ ^_	Record separator, block-mode terminator
US	37	31	1f	^_ ^_	Unit separator